



REPACK 610 & 616



REPACK 610



REPACK 616

REPACK 610 & 616

The REPACK is a useful tool for switching on and off non-dimmable devices such as flame effects, mirror balls, lighting fixtures with discharge lamps, black-light effects, moon flower effects etc. The Relay Pack is DMX-512 controlled and on the front panel there are six MCBs, mains switch, LED monitors and manual ON/OFF with six push buttons. It is supplied with one CEE 5X32A plug and socket for power supply. The unit features zero crossing switch-on and programmable switch-over level. The 3-digit numeric display shows the start address which can be selected from the corresponding buttons.

Also available with WIELAND and SOCAPEX outlets.

TECHNICAL SPECIFICATIONS	REPACKMODELS	
	610	616
NUMBER OF CHANNELS	6	6
CHANNEL CAPACITY (WATTS at 230V)	2300W	3680W
MAXIMUM CURRENT PER CHANNEL	10A	16A
SUPPLY VOLTAGE 220/240V AC 3 PHASES + NEUTRAL + EARTH ~ 50Hz	YES	YES
HOLD OF LAST DMX VALUE	YES	YES
RACK MOUNTING	YES	YES
TRUSS OR WALL MOUNTING	OPTIONAL	
DIMENSIONS IN MM (WxHxD)	483 x 88 x 255	

REAR SIDES



HARTING



CEE 17



SCHUKO - FRENCH
SWISS - DANISH

